



## HDM3065 Series

6 1/2 bit resolution;30 k/s high-speed sampling frequency, which makes it easy to capture transient signals; front and back multimeter input,measure a key switch;statistic analysis、 histogram and run chart display function;Double display measurement function,display 2 kinds of signal parameters at the same time;3A/10A current range;4.3 inch 64K LCD;0.1uV resolution,easy to use,parameters can be setted easily; 13 kinds of measure functions:DC Voltage, AC Voltage, DC current, AC current, 2 line resistance, 4 line resistance, capacitance, diode, connectivity, frequency, period, temperature.



- Real 6 1/2 bit reading resolution;
- Front and back 2 sets of multimeter input interface, measure can a key switch;
- Up to 30, 000 rdgs/s reading;
- Graph display function, trend drawing function to paperless record testing data, statistic information and histogram;
- Double display measurement function, display 2 kinds of signal parameters at the same time;
- True RMS AC voltage and AC current measure;
- 0.1 $\mu$ V resolution, easy to use, parameters can be set easily;
- Support dual display, Chinese and English menu;
- Built in help system, convenient access to information;
- 13 kinds of measure functions: DC Voltage, AC Voltage, DC current, AC current, 2 line resistance, 4 line resistance, capacitance, diode, connectivity, frequency, period, current range can be 10A;
- 4.3 inch 64K LCD;
- Safety standards: CAT II 300 V;
- Support standard SCPI Remote control command, upper computer software, Compatible with the latest mainstream multimeter command set;
- Configuration interface: USB Device, USB Host, LAN (HDM3065B), GPIB (HDM3065H).

## Real 6 1/2 bit reading resolution

4.3 inch 64K LCD;  
0.1 $\mu$ V resolution;  
Up to 30 , 000 rdgs/s reading;  
Digital multimeter with 2,200,000 counts.



## Front and back 2 sets of multimeter input interface

True RMS AC voltage and AC current measure;  
Double display measurement function,display 2 kinds of signal parameters at the same time;  
Support standard SCPI Remote control command、upper computer software.



## Graph display , trenddrawing ,statistic information and histogram

Support dual display, Chinese and English menu;

Double display measurement function,display 2 kinds of signal parameters at the same time.



# GraphPowerful Math statistic function

-dB/dBm measurement;

13 kinds of measure functions:DC Voltage, AC Voltage, DC current, AC current, 2 line resistance, 4 line resistance, capacitance, diode, connectivity, frequency, period, current range can be 10A.



Model	HDM3065H	HDM3065B	HDM3065A	
Resolution bit	6 1/2	6 1/2	6 1/2	
DCV basic precision	35 ppm	35 ppm	35 ppm	
Maximum reading rate	30,000 rdgs/s	30,000 rdgs/s	30,000 rdgs/s	
Memory	10,000 readings	10,000 readings	10,000 readings	10,
Double-display measurement function	√	√	√	
Statistical graph	Histogram, bar graph, trend graph	Histogram, bar graph, trend graph	Histogram, bar graph, trend graph	Histogram, bar graph, trend graph
Interface	USB、232/485、LAN、GPIB	USB、232/485、LAN	USB、232/485	USB、232/485

Input terminal	Front-panel Rear-panel	Front-panel Rear-panel	Front-panel Rear-panel	Front-panel Rear-panel	
Range <sup>2</sup> /frequency	24 hours <sup>3</sup>	90 days	1 year	2 years	
DC Voltage	TCAL±1°C	TCAL±5°C	TCAL±5°C	TCAL±5°C	
100 mV	0.0030+0.0030	0.0040+0.0035	0.0050+0.0035	0.0065+0.0040	
1 V	0.0020+0.0006	0.0030+0.0007	0.0040+0.0007	0.0055+0.0008	
10 V	0.0015+0.0004	0.0020+0.0005	0.0035+0.0005	0.0050+0.0005	
100 V	0.0020+0.0006	0.0035+0.0006	0.0045+0.0006	0.0060+0.0006	
1000 V	0.0020+0.0006	0.0035+0.0010	0.0045+0.0010	0.0060+0.0010	
True RMS AC voltage <sup>2, 5, 6</sup>					
100 mV、1 V、10 V、100 V and 750 V range					
5 Hz - 10 Hz	0.35+0.02	0.35+0.03	0.35+0.03	0.35+0.03	
10 Hz-20 KHz	0.04+0.02	0.05+0.03	0.06+0.03	0.07+0.03	
20 KHz-50 KHz	0.10+0.04	0.11+0.05	0.12+0.05	0.13+0.05	
50 KHz-100 KHz	0.55+0.08	0.60+0.08	0.60+0.08	0.60+0.08	
100 KHz-300 KHz	4.00+0.50	4.00+0.50	4.00+0.50	4.00+0.50	
Resistance <sup>7</sup>	Testing current				
100 Ω	1 mA	0.0030+0.0030	0.008+0.004	0.010+0.004	0.012+0.004
1 kΩ	1 mA	0.0020+0.0005	0.008+0.001	0.010+0.001	0.012+0.001
10 kΩ	100 μA	0.0020+0.0005	0.008+0.001	0.010+0.001	0.012+0.001
100 kΩ	10 μA	0.0020+0.0005	0.008+0.001	0.010+0.001	0.012+0.001
1 MΩ	5 μA	0.002+0.001	0.008+0.001	0.010+0.001	0.012+0.001
10 MΩ	500 nA	0.015+0.001	0.020+0.001	0.040+0.001	0.060+0.001
100 MΩ	500 nA  10 MΩ	0.300+0.010	0.800+0.010	0.800+0.010	0.800+0.010
DCcurrent	Potential drop of internal resistance				
100 μA	<0.11V	0.010+0.020	0.040+0.025	0.050+0.025	0.060+0.025

1 mA	<0.11V	0.007+0.006	0.030+0.006	0.050+0.006	0.060+0.006
10 mA	<0.05V	0.007+0.020	0.030+0.020	0.050+0.020	0.060+0.020
100 mA	<0.5V	0.010+0.004	0.030+0.005	0.050+0.005	0.060+0.005
1 A	<0.7V	0.050+0.006	0.080+0.010	0.100+0.010	0.120+0.010
3 A	<2.0V	0.180+0.020	0.200+0.020	0.200+0.020	0.230+0.020
10 A <sup>8</sup>	<0.5V	0.050+0.010	0.120+0.010	0.120+0.010	0.150+0.010
Capacitance <sup>15</sup>					
1.0000 nF		0.50+0.50	0.50+0.50	0.50+0.50	0.50+0.50
10.000 nF		0.40+0.10	0.40+0.10	0.40+0.10	0.40+0.10
100.00 nF		0.40+0.10	0.40+0.10	0.40+0.10	0.40+0.10
1.0000 µF		0.40+0.10	0.40+0.10	0.40+0.10	0.40+0.10
10.000 µF		0.40+0.10	0.40+0.10	0.40+0.10	0.40+0.10
100.00 µF		0.40+0.10	0.40+0.10	0.40+0.10	0.40+0.10
Range <sup>2</sup> /frequency	24hours <sup>3</sup>	90days	1year	2years	
	TCAL ± 1°C	TCAL ± 5°C	TCAL ± 5°C	TCAL :	
True RMS AC current <sup>2, 6, 9</sup>					
Potentia drop of internal res					
100 µA、1 mA、10 mA and 100 mA range					
3 Hz - 5 kHz		0.10+0.04	0.10+0.04	0.10+0.04	0.10+0.04
5-10kHz (typicalvalue)		0.10+0.04	0.10+0.04	0.10+0.04	0.10+0.04
1Arange	<0.7V				
3Hz-5kHz		0.10+0.04	0.10+0.04	0.10+0.04	0.10+0.04
5 kHz - 10 kHz (Typicalvalue)		0.10+0.04	0.10+0.04	0.10+0.04	0.10+0.04
3 A Range	<2.0V				
3 Hz - 5 kHz		0.23+0.04	0.23+0.04	0.23+0.04	0.23+0.04

5 kHz - 10 kHz (Typicalvalue)	0.23+0.04	0.23+0.04	0.23+0.04	0.23+0.04
10 A Range <sup>8</sup> <0.5V				
3 Hz - 5 kHz	0.15+0.04	0.15+0.04	0.15+0.04	0.15+0.04
5 kHz -10 kHz (Typicalvalue)	0.15+0.04	0.15+0.04	0.15+0.04	0.15+0.04
Connectivity				
1 kΩ	0.002+0.030	0.008+0.030	0.010+0.030	0.012+0.030
DiodeTesting <sup>10</sup>				
5 V	0.002+0.030	0.008+0.030	0.010+0.030	0.012+0.030
DCrate (Typicalvalue)  (Normalize precision input) + (Normalize reference accuracy)				
Temperature <sup>11</sup>				
PT100 (DIN/IEC751)	The probe accuracy+0.05°C			
5 kΩ thermistor	The probe accuracy+0.1°C			
Frequency : Technical Indicator± (%reading)	12.13			
100mV、1V、10、100V and 750 V range	<sup>14</sup>			
3 Hz-10 Hz	0.1	0.1	0.1	0.1
10 Hz-100 Hz	0.03	0.03	0.03	0.03
100 Hz-1 KHz	0	0.008	0.01	0.01
1 KHz-300 KHz	0.002	0.006	0.01	0.01
Square wave <sup>15</sup>	0.001	0.006	0.01	0.01
Extra Gate timeerror ± (%reading)	<sup>13</sup>			
Frequency	1 second	0.1 second	0.01 second	
3 Hz-40 Hz	0	0.2	0.2	
40 Hz-100 Hz	0	0.06	0.2	

100 Hz-1 KHz	0	0.02	0.2
1 KHz-300 KHz	0	0.004	0.03
Square wave <sup>15</sup>	0	0	0

1. For DC:technical indicators are valid after 60 minutes of preheating, set to 10 or 100NPLC in the integral period, and enable automatic zero setting. For AC:technical indicators are effective when preheating for 60 minutes, using slow ac filter and sine wave
2. All ranges have 20% overrange except for 1,000DCV、750ACV、10ADC、3AAC、10AAC and diode testing.
3. Relative to the calibration standard
4. Outside of the range of  $T_{CAL} \pm 5^{\circ}\text{C}$ , each degree (  $^{\circ}\text{C}$  ) increases a coefficient.
5. Technical indicators are valid when sinusoidal wave is input >5% range and >1mVrms. The 750ACV range is limited to  $8 \times 10^7 \text{v}\cdot\text{hz}$ . For inputs within 1% and 5% of range and frequency <50 kHz, add 0.1% of range additional error. For 50kHz to 100kHz, add 0.13% of range additional error
6. Low frequency performance:three filter Settings are provided:3Hz、20Hz、200Hz.The frequency beyond the filter setting has been specified, no additional errors will occur.
7. Technical indicators are suitable for 4 lines or 2 lines measurement ( operation bias returns to zero ) resistance measurement.If there is no mathematical null, 2 lines resistance measurement will increase  $0.2 \Omega$  additional error.
8. The 10A range is provided on the front connector only.Each amplifier adds a 2mA base current value, or input current >5Arms.
9. Technical indicators are valid when sine wave is input >1.5% range and >10  $\mu\text{AAC}$ .
10. Technical indicators are suitable for the voltage measured at the input end.1mA test current is typical.The change of current source will lead to the change of voltage drop of diode junction
11. The selected probe limits the actual measuring range and measurement errors.Probe accuracy has included all measurement and ITS-90 temperature

conversion errors.PT100Ro can be set to  $100\Omega \pm 5\Omega$ , to eliminate the original probe error.

12.Unless otherwise indicated, the technical indicators are valid after 60 minutes of warm-up and with sinusoidal input.Techincal indicators are suitable for 1s gate time.(7 bits)

13.Suitable for sinusoidal and square wave input  $\geq 100mV$ .For 10mV to 100mV inputs, multiply the reading error % by 10.

14.The range is 10% to 120% below 750ACV.

15.The square wave input is specified as 10Hz-300kHz.